Technical data sheet

Socket 0°, Connect 80, protective contact, double

Item number: 6120442





Protective contact socket with connection to side, double 0°, with increased touch protection, with screwless terminals, 2-pin, 16 A, 250 V \sim , with connection terminals to IEC 60884-1, suitable for the installation in Rapid 80 device installation trunking systems.

For installation in Rapid 45 trunking, device installation trunking, service poles, underfloor systems and desk boxes.





Polycarbonate

Master data

Item number	6120442
Туре	STD-D0C8 AL2
Description 1	Socket 0°, double
Description 2	protective contact, Connect 80
Manufacturer	OBO
Dimension	250V, 10/16A
Colour	Aluminium painted
Material	Polycarbonate
Smallest sales unit	1
Unit of quantity	Piece
Weight	13 kg
Weight unit	kg/100 pc.


Technical data sheet

Socket 0°, Connect 80, protective contact, double



Item number: 6120442





Technical data

Closable		
Olobabio	no	
Connection type	Screwless terminal	
Number of units	2	
Number of modules (for modular construction)	0	
Number of switchable sockets	0	
Number of poles	2	
Printed label/coding	Without printing	
Version for	double 0°	
Surface version	Matt	
Version for	SCHUKO	
Ejection mechanism	no	
Fastening type	Lock	
Labelling panel	no	
Operating temperature, max.	40 °C	
Operating temperature, min.	-5 °C	
increased touch protection	yes	
Error current protection	no	
For more difficult conditions (according to VDE)	no	
Power reserve	no	
Halogen-free	yes	
Insulated installation	no	
Hinged cover	no	
Coding	no	
Warning light	no	
With on/off switch	no	
With fine-wire fuse	no	
With functional lighting	no	
With orientation lighting	no	
Mounting type	Device installation duct	
Nominal voltage	250 V	
Nominal current	16 A	

Technical data sheet

Socket 0°, Connect 80, protective contact, double



Item number: 6120442

Technical data		
	Protection rating	Other
	Special power supply	Without special power supply
	Socket version	Protective contact
	Socket angle	0°
	Depth	42 mm
	Transparent	no
	Rotated central insert	no
	Surge protection	no